



















The standing wave observed can serve as a measure of the impedance mismatch between the CPS and the load. Reflection of the optical wave upon loads of various impedance would produce correspondingly stronger or weaker standing waves, with those of the open-circuit and short-circuit loads being the most pronounced. The absence of a standing wave would indicate perfect impedance matching between the CPS and the load, and, correspondingly, maximum power transfer. The *s*-SNOM characterization method described here provides a way to determine the relative magnitude of impedance mismatch to practical loads, and thus serves as a design tool enabling integrated infrared antenna systems with high coupling efficiency. The characteristic impedance of the transmission line  $Z_0$  can be determined from the reflection coefficient,  $\Gamma = (Z_L - Z_0)/(Z_L + Z_0)$ , if a load with a known impedance  $Z_L$  is used. If the impedance of the load is unknown, a parametric study of identical CPS with loads of slightly varying geometries can be used to analytically determine the characteristic impedance of the transmission line.